



BX316 GNSS Kit

With 2W/460MHz Radio

Overview

BX316 Kit consists of BX316 Basic and 2W Radio Option. BX316 GNSS receiver is a dual frequency GNSS RTK receiver providing accurate positioning, raw measurement output, and heading information. It offers real-time, cost-efficient, and cm-level positioning as well as flexible interfaces.

2W Radio option provides reliable data communications between 457 MHz and 467 MHz for mission-critical applications where a combination of stability, superior performance and long distance are required. Equipped with dual antenna design for precise heading, the BX316 Kit is ideal for precision navigation, precision agriculture, and surveying.

Key Features

Supports RTK positioning mode or RTK positioning + heading mode. The two modes are software configurable

Supports 384 channels

Command compatible with NovAtel protocol

Supports 20Hz RTK solution updates and raw data outputs

Supports in-built 4GB memory, which makes data collection easy

Supports PPS output and event mark input

Serial ports with LVTTTL or RS232

External antenna inputs through SMA connectors

Data output: NMEA-0183 and Tersus binary format

Correction: RTCM 2.x/3.x/CMR/CMR+

Easy to integrate with Pixhawk and other autopilots

Supports large range of input power conditions



Note: If users want to customize the product portfolio, please contact sales@tersus-gnss.com by email.



Technical Specifications - BX316 enclosure

Performance

Signal Tracking for Primary Antenna:	
GPS L1/L2, GLONASS L1/L2, BeiDou B1/B2	
Signal Tracking for Secondary Antenna:	
GPS L1+GLONASS L2 or GPS L1+BeiDou B2	
GNSS Channels:	384
Single Point Positioning Accuracy (RMS):	
– Horizontal:	1.5m
– Vertical:	3.0m
RTK Positioning Accuracy (RMS):	
– Horizontal:	10mm+1ppm
– Vertical:	15mm+1ppm
Observation Accuracy (zenith direction):	
– C/A Code:	10cm
– P Code:	10cm
– Carrier Phase:	1mm
Heading Accuracy:	
– 1m Baseline (RMS):	0.15°
Time To First Fix (TTFF):	
– Cold Start:	<50s
– Warm Start:	<30s
Timing Accuracy (RMS):	20ns
Velocity Accuracy (RMS):	0.03m/s
Initialization (typical):	<10s
Initialization Reliability:	>99.9%
Correction:	RTCM 2.x/3.x/CMR/CMR+
Max. Update Rate:	20Hz
Input Voltage:	5V~12V DC
Power Consumption (typical):	3.5W
Active Antenna Input Impedance:	50Ω
Storage:	In-built 4GB memory

Communication

Serial Ports:	LVTTTL x2 or RS232 x2
USB Ports:	USB device x1
CAN Ports:	ISO/DIS 11898 x1*
PPS Ports:	LVTTTL x1
Event Mark:	LVTTTL x1

* This port's function is related to firmware version.

Physical

Size:	111x57x24mm
Weight:	154g
Antenna Connector:	SMA female x2
COM Baud Rate:	Up to 460800bps
Operating Temperature:	-40°C ~ +85°C

Website | www.tersus-gnss.com
Sales Inquiry | sales@tersus-gnss.com
Technical Support | support@tersus-gnss.com



Technical Specifications

- 2W Radio RS460

General

Frequency Range:	457MHz~467MHz
Band Width:	10 MHz
Channel Width:	25KHz
Operation Voltage:	5V~12V
Power Consumption (typical):	
– Transmitting 2W:	6.5W@DC5.5V
– Transmitting 1W:	4W@DC5.5V
– Receiving:	< 400mW@DC5.5V
Dimension:	107x62x26.6mm
Weight:	≈213g
Operation Temperature:	-30°C ~ +60°C
Storage Temperature:	-40°C ~ +85°C
Antenna Port:	TNC Female
Antenna Impedance:	50Ω
VSMR:	≤ 1.5

Transmitter


Frequency Stability (at 25°C):	≤±1.5ppm
Configurable Channels:	10
Adjacent Channel Selectivity:	≥ 60dB
RF Output Power:	
– High Power Level (2W):	33.5±0.5dBm@DC5.5V
– Low Power Level (1W):	30±0.5dBm@DC5.5V

Modem

Air Baud Rate:	9600bps @ 25KHz
Modulation Type:	GMSK
RF Sensitivity:	Better than 13dB @ -119dBm
Decode Sensitivity:	-116 dBm BER 10E-5 @ 9600bps
Protocol:	Transparent EOT, TT450S and Tersus

Interface (Pin) Definition

Type:	RS232
Pin 1:	Power Ground, GND
Pin 2:	Power Ground, GND
Pin 3:	Power, 5V~12V DC
Pin 4:	RXD
Pin 5:	TXD



Overview of Interface (Pin)

