

Tersus GNSS

Oscar-TAP GNSS Receiver

Overview

The Oscar-TAP GNSS Receiver adopts satellite-based precise point positioning service developed by Tersus GNSS, which allows users to achieve centimeter-level high-precision positioning worldwide. With TAP, the GNSS rover receiver will not need to work with the local RTK base station or CORS, but directly receives corrections broadcast by the satellites, such as ephemeris error, satellite clock error, etc. It supports calibration-free tilt compensation function which is immune to magnetic disturbances, leveling pole is not required. Easy configuration with 1.54 inch interactive screen on Ultimate versions. With an internal high-performance multi-constellation and multi-frequency GNSS board, the Oscar-TAP GNSS Receiver can provide high accuracy and stable signal detection. The high-performance antenna can speed up the time to first fix (TTFF) and improve anti-jamming performance. The built-in large capacity battery is detachable, two batteries support up to 16 hours of field work in 4G/3G/2G network and Rover radio mode. The built-in UHF radio module supports long distance communication. The rugged housing protects the equipment from challenging environments.

Oscar-TAP meets the demand of centimeter-level high-precision positioning in areas without or with poor network coverage, such as oceans, deserts, mountains, high altitudes, etc.

The Oscar-TAP GNSS Receiver has two versions: Ultimate and Basic. It provides selectivity for the requirement from different users.

Key Features

- ✓ Multiple constellations and frequencies
 - GPS L1 C/A, L2C, L2P, L5
 - GLONASS L1 C/A, L2 C/A
 - BeiDou B1, B2, B3, support BDS-3
 - Galileo E1, E5a, E5b
 - QZSS L1 C/A, L2C, L5
 - SBAS supports WAAS, EGNOS, GAGAN, SDCM, MSAS(Optional for Oscar-TAP Basic)
 - L-Band
- ✓ Supports 1792 channels
- ✓ 410-470MHz UHF radio, 4G network, Wi-Fi, Bluetooth, NFC
- ✓ Tilt compensation without calibration, immune to magnetic disturbances⁽¹⁾
- ✓ 16GB/8GB internal storage
- ✓ Up to 16 hours working in 4G/3G/2G network and Rover radio mode
- ✓ IP68-rated dust- & waterproof enclosure, for reliability in harsh environmental conditions
- ✓ Free subscription of Tersus Caster Service (TCS): transmit the correction data from Oscar Base to Rover
- ✓ With worldwide coverage, TAP can be used as long as there is a good vision
- ✓ No need to use the network to receive corrections with TAP
- ✓ High signal stability, which guarantees uninterrupted transmission for 24 hours a day
- ✓ It can be widely used in autonomous driving precision agriculture, and disaster monitoring and so on



Tersus GNSS

Oscar-TAP GNSS Receiver

Technical Specifications

Performance

Signal Tracking:	
GPS L1 C/A, L2C, L2P, L5	
GLONASS L1 C/A, L2 C/A	
BDS B1, B2, B3, supports BDS-3	
Galileo E1, E5a, E5b	
QZSS L1 C/A, L2C, L5	
SBAS ⁽²⁾ supports WAAS, EGNOS, GAGAN, SDCM, MSAS L-band	
Channels:	1792
Single Point Positioning Accuracy (RMS):	
- Horizontal:	1.5m
- Vertical :	3.0m
DGPS Positioning Accuracy (RMS):	
- Horizontal:	0.25m
- Vertical:	0.5m
High-Precision Static (RMS):	
- Horizontal:	2.5mm+0.1ppm
- Vertical:	3.5mm+0.4ppm
Static & Fast Static (RMS):	
- Horizontal:	2.5mm+0.5ppm
- Vertical:	5mm+0.5ppm
Post Processed Kinematic (RMS):	
- Horizontal:	2.5mm+1ppm
- Vertical:	5mm+1ppm
Real Time Kinematic (RMS):	
- Horizontal:	8mm+1ppm
- Vertical:	15mm+1ppm
Initialization (Typical):	4s ⁽³⁾
Initialization Reliability:	>99.99% ⁽⁴⁾
Network Real Time Kinematic (RMS):	
- Horizontal:	8mm+0.5ppm
- Vertical:	15mm+0.5ppm
Observation Accuracy (zenith direction):	
- C/A Code:	10cm
- P Code:	10cm
- Carrier Phase:	1mm

Time To First Fix (TTFF):	
- Cold Start:	<35s
- Warm Start:	<10s
Re-acquisition:	<1s
Tilt Compensation Accuracy (No tilt angle limit):	
	≤2cm(within 60°)
Timing Accuracy (RMS):	20ns
Velocity Accuracy (RMS):	0.03m/s
TAP Positioning Accuracy (RMS):	
- Horizontal:	15cm
- Vertical:	30cm
TAP Convergence Time:	3 minutes
TAP Coverage:	Global
TAP Signal Stability:	99.99%

System & Data

Operating System:	Linux
Storage:	Built-in 16GB/8GB ⁽¹⁾
Data Format:	CMR, CMR+ (GPS only),RTCM 2.x/3.x
Data Output:	RINEX, NMEA-0183, Tersus binary
Data Update Rate:	20Hz

Software Support

Tersus Nuwa

Communication

Cellular:	4G LTE/WCDMA/GSM
Cellular Bands ⁽⁵⁾ :	
	FDD LTE 1,3,7,8,20,28A 2,4,5,12,13
	TDD LTE 38,40,41
	WCDMA 1,8 2,5
	GSM3,8
Network Protocols:	Ntrip Client, Ntrip Server,TCP Tersus Caster Service (TCS)

Technical Specifications

Wi-Fi:	802.11b/g
Bluetooth:	4.1
Internal Radio	
RF Transmit Power:	0.5W/1W/2W
Frequency Range:	410MHz ~ 470MHz
Operating Mode:	Half-duplex
Channel Spacing:	12.5KHz / 25KHz
Modulation Type:	GMSK, 4FSK
Air Baud Rate:	4800 / 9600 / 19200bps
Distance (Typical):	>5km
Radio Protocols:	TrimTalk450, TrimMark 3, South, Transparent, Satel
Wired Communication	
USB OTG:	USB 2.0 x1
Serial Ports:	RS232 x1
COM Baud Rate:	up to 921600bps

Electrical

Input Voltage:	9~28V DC
Power Consumption (Typical):	
Network or Radio Receive Mode:	≈ 5W
Radio Transmit Mode (0.5W):	≈ 8W
Radio Transmit Mode (1W):	≈ 9W
Radio Transmit Mode (2W):	≈ 11W
Lithium Battery:	7.4V 6400mAh x2 ⁽⁶⁾
Battery Charging Temperature:	+10°C ~ +45°C
Battery Working Time:	up to 8 hours ⁽⁶⁾

Note:

(1) Details refer to performance comparison table.

(2) SBAS optional for Oscar-TAP Basic.

(3) The initialization time depends on various factors, including the number of satellites, observation time, atmospheric conditions, multi-path, obstructions, satellite geometry, etc.

(4) The initialization reliability for Oscar-TAP Ultimate is 99.99%, for Basic is 99.9%. May be affected by atmospheric conditions, signal multipath, and satellite geometry.

(5) Depending on version. In order Europe | American version.

(6) Oscar-TAP uses one battery at a time, the other is a substitute. Each battery lasts up to 8 hours when Oscar-TAP works in 4G/3G/2G network and Rover radio mode. Two batteries add up to 16 hours of continuous use. The working time of the battery is related to the working environment, working temperature and battery life.

(7) The actual size/weight may vary depending on the manufacturing process and measurement method.

(8) Smart antenna: A compact and high precision product with and robust positioning accuracy.

Physical

Display:	1.54" OLED ⁽¹⁾
Dimension:	157x157x103mm ⁽⁷⁾
Weight:	≈ 1.2kg (without battery) ≈ 1.4kg (with a battery) ⁽⁷⁾
Operating Temperature:	-40°C ~ +70°C
Storage Temperature:	-55°C ~ +85°C
Relative Humidity:	100% not condensed
Dust- & Waterproof:	IP68
Pole Drop onto Concrete:	2m
Vibration:	MIL-STD-810G, FIG 514.6C-1

Technical Specifications

Oscar-TAP Version	Ultimate	Basic
Picture		
Channels	1792	1792
GPS	L1 C/A, L2C, L2P, L5	L1 C/A, L2C, L2P, L5
GLONASS	L1 C/A, L2 C/A	L1 C/A, L2 C/A
BeiDou	B1, B2, B3 (BDS-3)	B1, B2, B3 (BDS-3)
Galileo	E1, E5a, E5b	E1, E5a, E5b
QZSS	L1 C/A, L2C, L5	L1 C/A, L2C, L5
SBAS ⁽²⁾	WAAS, EGNOS, GAGAN, SDCM, MSAS	WAAS, EGNOS, GAGAN, SDCM, MSAS
L-Band	✓	✓
GNSS antenna ⁽⁸⁾	Integrated	Integrated
Buttons	FN, ON/OFF	FN, ON/OFF
Display	1.54"OLED	×
LED indicators	Satellite, Tilt, Correction data, Power	Satellite, Static, Correction data, Power, Bluetooth, Solution status
Bluetooth	✓	✓
NFC	✓	✓
UHF radio	✓	✓
4G	✓	✓
Tilt compensation (IMU)	✓	✗
Electronic bubble	✓	✓
Memory	16GB	8GB
USB OTG	✓	✓
Battery capacity	7.4V 6400mAh x2	7.4V 6400mAh x2
Smart battery with power display	✓	✓
Warranty period	TWO Years	ONE Year

Website: www.tersus-gnss.com
Sales Inquiry: sales@tersus-gnss.com
Technical Support: support@tersus-gnss.com

Information is subject to change without notice.
 © Copyright 2024 Tersus GNSS Inc.